

PWR7205

Features

The PWR7205 is designed for use with stepper motor drivers such as the DR8010™ and DM8010™ drivers.

- AC input voltage jumper selectable between 115 VAC and 230 VAC.
- Fused DC output.
- Threaded mounting holes for easy installation

Electrical Specifications

Input voltage 115/230 VAC

Current consumption 3 amps at 115 volts/1.5 amps at 230 volts

Voltage outputs 72 volts unregulated at 5 Amps

Physical dimensions 6.5" w X 5.0" d X 4.25" h

Working temperature range 32°F ~ 122° F (0° C ~ 50° C)

Wiring Connections

Configuration

For 115 VAC input, place the jumpers across 3 & 4 ,and across 5 & 6.

For 230 VAC input, place one jumper across 4 & 5.

